

[Get a Quote](#)

## Overview

Cisco® Catalyst® 9115 Series Wi-Fi 6 Access Points are the next generation of enterprise access points. They are resilient, secure, and intelligent. C9115AXI-H is the Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, H Domain.

## Quick Specification

Table 1 shows the quick specification of C9115AXI-H.

Product Code	C9115AXI-H
Description	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, H Domain
Software	<ul style="list-style-type: none"> <li>• Cisco Unified Wireless Network Software Release 8.9 or later</li> <li>• Cisco IOS® XE Software Release 16.11 or later</li> </ul>
Supported wireless LAN controllers	<ul style="list-style-type: none"> <li>• Cisco Catalyst 9800 Series Wireless Controllers</li> <li>• Cisco 3500, 5520, and 8540 Series Wireless Controllers and Cisco Virtual Wireless Controller</li> </ul>
Dimensions (W x L x H)	8.0 x 8.0 x 1.5 in. (20.3 x 20.3 x 3.8 cm)
System memory	<ul style="list-style-type: none"> <li>• 2048 MB DRAM</li> <li>• 1024 MB flash</li> </ul>
Frequency band and 20-MHz operating channels	<p>H (H regulatory domain):</p> <ul style="list-style-type: none"> <li>• 2.412 to 2.472 GHz; 13 channels</li> <li>• 5.180 to 5.320 GHz; 8 channels</li> <li>• 5.745 to 5.825 GHz; 5 channels</li> </ul>

Figure 1 shows the appearance of C9115AXI-H.



## Product Details

### Supported Platforms

Table 2 shows the supported platforms and software.

Supported wireless LAN controllers and Software	Recommended Model
Cisco 3500 Series Wireless Controllers	<a href="#">AIR-CT3504-K9</a>
Cisco 5520 Series Wireless Controllers	<a href="#">AIR-CT5520-K9</a>
Cisco 8540 Series Wireless Controllers	<a href="#">AIR-CT8540-K9</a> AIR-CT8540-1K-K9
Cisco 9800 series Wireless Controllers	C9800-40-K9 C9800-80-K9
Cisco Virtual Wireless Controller	/
Cisco Unified Wireless Network Software Release 8.9 or later	/
Cisco IOS @ XE Software Release 16.11 or later	/

### Compare to Similar Items

Table 3 shows the comparison of Cisco AP 9115I series.

SKU	Description
<a href="#">C9115AXI-A</a>	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, A Domain
<a href="#">C9115AXI-B</a>	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, B Domain
C9115AXI-D	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, D Domain
<a href="#">C9115AXI-E</a>	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, E Domain
C9115AXI-G	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, G Domain
C9115AXI-H	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, H Domain

### Get More Information

Do you have any question about the C9115AXI-H?

Contact us now via [info@hi-network.com](mailto:info@hi-network.com).

## Specification

<b>C9115AXI-H Specification</b>	
Description	Cisco Catalyst 9115AX Series Access Point, Internal antenna; Wi-Fi 6; 4x4:4 MIMO, H Domain
Software	<ul style="list-style-type: none"> <li>• Cisco Unified Wireless Network Software Release 8.9 or later</li> <li>• Cisco IOS® XE Software Release 16.11 or later</li> </ul>
Supported wireless LAN controllers	<ul style="list-style-type: none"> <li>• Cisco Catalyst 9800 Series Wireless Controllers</li> <li>• Cisco 3500, 5520, and 8540 Series Wireless Controllers and Cisco Virtual Wireless Controller</li> </ul>
802.11n version 2.0 (and related) capabilities	<ul style="list-style-type: none"> <li>• 4x4 MIMO with four spatial streams</li> <li>• Maximal Ratio Combining (MRC)</li> <li>• 802.11n and 802.11a/g beamforming</li> <li>• 20- and 40-MHz channels</li> <li>• PHY data rates up to 890 Mbps (40 MHz with 5 GHz and 20 MHz with 2.4 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 Dynamic Frequency Selection (DFS)</li> <li>• Cyclic Shift Diversity (CSD) support</li> </ul>
802.11ac	<ul style="list-style-type: none"> <li>• 4x4 downlink MU-MIMO with four spatial streams</li> <li>• MRC</li> <li>• 802.11ac beamforming</li> <li>• 20-, 40-, 80-, and 160-MHz channels</li> <li>• PHY data rates up to 3.47 Gbps (160 MHz with 5 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 DFS</li> <li>• CSD support</li> </ul>
802.11ax	<ul style="list-style-type: none"> <li>• 4x4 downlink MU-MIMO with four spatial streams</li> <li>• Uplink/downlink OFDMA</li> <li>• TWT</li> <li>• BSS coloring</li> <li>• MRC</li> <li>• 802.11ax beamforming</li> <li>• 20-, 40-, 80-, and 160-MHz channels</li> <li>• PHY data rates up to 5.38 Gbps (160 MHz with 5 GHz and 20 MHz with 2.4 GHz)</li> <li>• Packet aggregation: A-MPDU (transmit and receive), A-MSDU (transmit and receive)</li> <li>• 802.11 DFS</li> <li>• CSD support</li> </ul>
Integrated antenna	<ul style="list-style-type: none"> <li>• 2.4 GHz, peak gain 3 dBi, internal antenna, omnidirectional in azimuth</li> <li>• 5 GHz, peak gain 6 dBi, internal antenna, omnidirectional in azimuth</li> </ul>
External antenna (sold separately)	<ul style="list-style-type: none"> <li>• Cisco Catalyst 9115AXE Access Points are certified for use with antenna gains up to 6 dBi (2.4 GHz and 5 GHz)</li> <li>• Cisco offers the industry's broadest selection of antennas, delivering optimal coverage for a variety of deployment scenarios</li> </ul>
Interfaces	<ul style="list-style-type: none"> <li>• 1x 100, 1000, 2500 Multigigabit Ethernet (RJ-45) – IEEE 802.3bz</li> <li>• Management console port (RJ-45)</li> <li>• USB 2.0 (enabled via future software)</li> </ul>

Indicators	<ul style="list-style-type: none"> <li>● Status LED indicates boot loader status, association status, operating status, boot loader warnings, and boot loader errors</li> </ul>
Dimensions (W x L x H)	<ul style="list-style-type: none"> <li>● Access point (without mounting brackets): C9115I: 8.0 x 8.0 x 1.5 in. (20.3 x 20.3 x 3.8 cm)</li> </ul>
Input power requirements	<ul style="list-style-type: none"> <li>● 802.3at Power over Ethernet Plus (PoE+), 802.3bt Cisco Universal PoE (Cisco UPOE+, Cisco UPOE®)</li> <li>● Cisco power injector, AIR-PWRINJ6=</li> <li>● 802.3af PoE</li> <li>● Cisco power injector, AIR-PWRINJ5= (Note: This injector supports only 802.3af)</li> </ul> <p>Note: When 802.3af PoE is the source of power, both 2.4-GHz and 5-GHz radios will be reduced to 2x2 and Ethernet downgraded to 1 Gigabit Ethernet. In addition, the USB port will be off.</p>
Environmental	<p>Cisco Catalyst 9115AXI</p> <ul style="list-style-type: none"> <li>● Nonoperating (storage) temperature: -22° to 158°F (-30° to 70°C)</li> <li>● Nonoperating (storage) altitude test: 25°C, 15,000 ft.</li> <li>● Operating temperature: 32° to 122°F (0° to 50°C)</li> <li>● Operating humidity: 10% to 90% (noncondensing)</li> <li>● Operating altitude test: 40°C, 9843 ft.</li> </ul> <p>Note: When the ambient operating temperature exceeds 40°C, the access point will shift from 4x4 to 2x2 on both the 2.4-GHz and 5-GHz radios, uplink Ethernet will downgrade to 1 Gigabit Ethernet, and the USB interface will be disabled.</p>
System memory	<ul style="list-style-type: none"> <li>● 2048 MB DRAM</li> <li>● 1024 MB flash</li> </ul>
Available transmit power settings	<p>2.4 GHz</p> <ul style="list-style-type: none"> <li>● 23 dBm (200 mW)</li> <li>● 20 dBm (100 mW)</li> <li>● 17 dBm (50 mW)</li> <li>● 14 dBm (25 mW)</li> <li>● 11 dBm (12.5 mW)</li> <li>● 8 dBm (6.25 mW)</li> <li>● 5 dBm (3.13 mW)</li> <li>● 2 dBm (1.56 mW)</li> <li>● -1dBm (0.79mW)</li> <li>● -4dBm(0.39mW)</li> </ul> <p>5 GHz</p> <ul style="list-style-type: none"> <li>● 26 dBm (400 mW)</li> <li>● 23 dBm (200 mW)</li> <li>● 20 dBm (100 mW)</li> <li>● 17 dBm (50 mW)</li> <li>● 14 dBm (25 mW)</li> <li>● 11 dBm (12.5 mW)</li> <li>● 8 dBm (6.25 mW)</li> <li>● 5 dBm (3.13 mW)</li> <li>● 2 dBm (1.56 mW)</li> <li>● -1dBm (0.79mW)</li> <li>● -4 dBm (0.39 mW)</li> </ul>
Frequency band and 20-MHz operating channels	<p>H (H regulatory domain):</p> <ul style="list-style-type: none"> <li>● 2.412 to 2.472 GHz; 13 channels</li> <li>● 5.180 to 5.320 GHz; 8 channels</li> <li>● 5.745 to 5.825 GHz; 5 channels</li> </ul>

## Want to Buy

---

Get a Quote



[Learn More](#) about Hi-Network



[Search](#) our Resource Library



[Follow](#) us on LinkedIn



Contact for [Sales or Support](#)

## Contact HI-NETWORK.COM For Global Fast Shipping

---

HongKong Office Tel: +00852-66181601

HangZhou Office Tel: +0086-571-86729517

Email: [info@hi-network.com](mailto:info@hi-network.com)

Skype: [echo.hinetwork](https://www.skype.com/people/echo.hinetwork)

WhatsApp Business: +8618057156223